PHU9 SSI ABSOLUTE MULTITURN ENCODER



• Version Heavy-Duty, Ø 30mm through shaft, reduction hubs available

Sensata

Technologies

- Robustness and excellent resistance to shocks / vibrations
- High performances in temperature –20°C to +80°C
- Isolated SSI interface, clock from 100 to 500 kHz
- Universal electronic circuits from 5 to 30Vdc
- Protection against short-circuits and inversion of polarity
- High resolutions available: 8192 (13 bits) per turn
- Turn counting up to 65 536 (16 bits)
- 2 inputs : DIRECTION and RAZ
- Available with incremental channels 2048 points 5 to 30 Vdc

Θ

MECHANICAL CHARACTERISTICS

	Cover : steel				
Material	Body : aluminum				
	Shaft : stainless steel				
Bearings	6 807 serial				
Maximum loads	Axial : 50 N				
Maxillulii loaus	Radial : 80 N				
Shaft inertia	$\leq 55.10^{-6} \text{ kg.m}^2$ $\leq 25.10^{-3} \text{ N.m}$ $6 000 \text{ min}^{-1}$ $6 000 \text{ min}^{-1}$ Viton $\leq 500 \text{ m.s}^{-2} (\text{during 6 ms})$ $\leq 100 \text{ m.s}^{-2} (10 \dots 2 000 \text{ Hz})$				
Torque					
Permissible max. speed					
Continuous max. speed					
Shaft seal					
Shock (EN60068-2-27)					
Vibration (EN60068-2-6)					
EMC	EN 61000-6-4, EN 61000-6-2				
Isolation	100V (1 min)				
Weight (approx.)	0,700 kg				
Operating temperature	- 20 + 80 °C (encoder T°)				
Storage temperature	- 20 + 80 °C				
Protection(EN 60529)	IP 65				
Torque (ring pressure screw)	4.5 N.m				
Theoretical mechanical lifetime 10º turns (Faxial / Fradial)	25 N / 40 N : 140				
i neoretical mechanical metime fo [°] turns (raxial / fradial)	50 N / 80 N : 17				




ELECTRICAL CHARACTERISTIC

Input signal clock CLK	per opto-coupler
Output signal DATA	line - driver selon RS422
Clock frequency CLK	100kHz – 500kHz
Precision	± 1/2 LSB (13 bits)
Power supply	5 – 30Vdc
Introduction	<1s
Cons. without load	< 100mA (typically 50-60mA at 24Vdc)
Position refresh	< 200µs







Transmission	Transmission up to 400m* at 100kHz in function of the cable characteristics				
Cable	High security of transmission by using shielded cable and twisted pairs				

*Consult us for length > 100m

SSI CONNECTION (TYPE S6 : BEI SENSORS STANDARD)

Туре	Vcc	Gnd	Clk+	Data+	RAZ	Data-	Clk-	DIRECTION
S 6	1	2	3	4	5	6	7	9
S 8	8	1	3	2	6	10	11	5
S 5	BN/GN Brown/Green	WH/GN White/Green	GN Green	GY Grey	BU Blue	PK Pink	BN Brown	WH White


Note : Do not connect other pinouts, connect DIRECTION and RAZ to a potential (RAZ at OV if not used)

Data output RS422

Isolated Clk input

DIRECTION input


RAZ / RAX input








PHU9_20 connection S6R / S8R (radial M23) , with reduction hub 9418 mounted in the shaft



PHU9 connection S6R / S8R (radial M23), with reduction hubs 9418 and DAC 9445/009* on the body



 * Accessory to be ordered separately

Page 3



(Contact the factory for special versions, ex: special flanges, connections, electronics...)

PHU9	_ 30	//	Р	SS	G	// 13	B12	D5_//S6	i R
Model									
PHU9									
Shaft Ø 🛛 —									
30 : 30mm Reduction hub available									
Supply									
•: 5 to 30Vdc									
Output stage									
SSI without parity									
Code ——									
Binary Gray									
Resolution -									
13 Resolution 13: 13 Bits	B12 Nb of turn: 12	D5 bits Nb	data: 25 bits	;					
Connection -									
S6 : M23 12pins CW S8: M23 12pins CCW S5R: PUR cable									
Orientation -									
R · radial									

R : radial Example : **R020 :** radial cable 2m

AGENCY APPROVALS & CERTIFICATES



Vade In Franc

Page 4

Sensata Technologies, Inc. ("Sensata") data sheets are solely intended to assist designers ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DATA SHEETS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE THEROF.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA.

CONTACT US

+1 (800) 350 2727 sales.beisensors@sensata.com **Europe, Middle East & Africa** +33 (3) 88 20 8080 position-info.eu@sensata.com **Asia Pacific** sales.isasia@list.sensata.com China +86 (21) 2306 1500 Japan +81 (45) 277 7117 Korea +82 (31) 601 2004 India +91 (80) 67920890 **Rest of Asia** +886 (2) 27602006 ext 2808